

# LBB 1995/00 - LBB 1999/00 Plena Voice Alarm System Remote Control



Security Systems



- Remote Control of the Voice Alarm System
- Emergency (EMG) microphone
- EMG and background (BGM) zone selections
- EMG state and fault indicators
- Control outputs for EMG and Fault state Front panel zone selection for BGM and call station zone selection for calls

The Plena Voice Alarm Remote Control panels offer operational control at up to two remote locations. The main RC unit offers the front panel of the voice alarm controller, while the RC extensions offer the control of the routers. Both remote controls (LBB 1996 & LBB 1997) are available as a kit to manufacture tailor made solutions. Also available is a fireman's panel that features large illuminated buttons and an all call functionality.

## Functions

The remote control is an exact match to the voice alarm controller with all controls and indicators at the same location. The remote control has BGM zone selection but not source selection, volume and tone controls. The remote control extension is a match to the router.

The volume units (VU) meter shows the presence and level of the calls that are running in the system. The fault indicators show detailed information of a fault in the system. Connection to the Bosch Voice Alarm System is done via standard shielded CAT 5 cable and RJ45 connectors. Included in the delivery are rack mount brackets that can also be used to mount the units to a rear wall with spacing for cables and even to a flat surface above or below the units.

The kits LBB 1998 & LBB 1999 are a functional match to the remote control and the RC extension, with connectors on the front panel instead of controls and indicators. With these kits it is possible to reliably build a custom control unit with confidence and ease. The electrical connections are printed on front and rear panels. A 24 VDC output is available to supply power to external LEDs and relays, so no external power supply is required for that purpose. An LED VU-meter allows for monitoring of the master output.

The fire panel, remote control and remote control kit function on an external 24V power supply. The RC extension and extension kit are powered by the interconnecting CAT-5 (shielded) cable.

**Parts Included**

Quantity	Component
1	LBB 1995/00 – LBB 1999/00
1	EMG microphone and cable (except extension)
1	1 m CAT-5 cable
2	19" mounting brackets
1	EMG mic mounting clip
1	Release notes
1	Plena CD with configuration software, installation and user instructions, audio tools, free music and more

**Certifications and Approvals**

EMC emission	Acc. to EN 55103-1
EMC immunity	Acc. to EN 55103-2

Technical Specifications	
<b>Electrical</b>	
24 V input	24 VDC, +20% / -10%
battery current	Typical – max (indicator test)
LBB 1995/00	100 mA – 250 mA
LBB 1996/00	100 mA – 250 mA
LBB 1997/00	50 mA – 200 mA
LBB 1998/00	100 mA – 250 mA
LBB 1999/00	50 mA – 200 mA
<b>Performance*</b>	
<b>Relays</b>	
Priority relay contacts	30 V, 1 A
Emergency relay contacts	30 V, 1 A
DC supply output voltage	24 V, 200 mA max
<b>LEDs / LAMPs</b> (KITS)	
LEDs on internal power	5 mA max
External power	50V – 200 mA max
Type	Open collector pull down

Environmental	
Operating temperature range	-10°C to +55°C
Storage temperature range	-40°C to +70°C
Relative humidity	<95%
General	
Dimensions	
LBB 1995/00	134 x 430 x 90 mm (19" wide, 3U high)
LBB 1996/00	134 x 430 x 90 mm (19" wide, 3U high)
LBB 1997/00	88 x 430 x 90 mm (19" wide, 2U high)
LBB 1998/00	134 x 430 x 90 mm (19" wide, 3U high)
LBB 1999/00	88 x 430 x 90 mm (19" wide, 2U high)
Weight approx.	3 kg

\*) Technical performance data acc. to IEC60268-3

Ordering Information
<b>Model &amp; Description</b>
LBB 1995/00 Plena Voice Alarm System Fireman's panel All call EVAC Remote Control with microphone
LBB 1996/00 Plena Voice Alarm Remote Control 6 zone Voice Alarm Controller remote control with microphone
LBB 1997/00 Plena Voice Alarm System Remote Control Extension 6 Zone Voice Alarm Router remote control
LBB 1998/00 Plena Voice Alarm System Remote Kit Kit for 6 Zone Voice Alarm controller remote control
LBB 1999/00 Plena Voice Alarm System Remote Control Extension Kit for 6 Zone Voice Alarm router remote control

**Americas:**  
 Bosch Security Systems  
 130 Perinton Parkway  
 Fairport, New York, 14450, USA  
 Phone:+1 585 223 4060  
 +1 800 289 0096  
 security.sales@us.bosch.com  
 http://www.boschsecurity.us

**Europe, Middle East, Africa:**  
 Bosch Security Systems B.V.  
 P.O. Box 80002  
 5600 JB Eindhoven, The Netherlands  
 Phone:+31 (0) 40 27 83955  
 Fax:+31 (0) 40 27 86668  
 emea.securitysystems@bosch.com  
 http://www.boschsecurity.com

**Asia-Pacific:**  
 Bosch Security Systems Pte Ltd  
 38C Jalan Pemimpin  
 Singapore 577180  
 Phone:+65 6319 3450  
 Fax:+65 6319 3499  
 apr.securitysystems@bosch.com  
 http://www.boschsecurity.com

